


Alarm clock Pro



Buttons and controls



1 – 3.5 mm external trigger input, 2 – Bed shaker
3 – Landline telephone, 4 – Power supply

Technical specifications

In the box

- BE1370 Pro alarm clock
- BE1272 Bed shaker with sound
- Power supply
- 4 x 1.2 V AAA NiMH batteries

Power and battery

- Mains power
7.5 V DC / 1000 mA
External power supply unit
- Backup batteries
4 x 1.2 V AAA NiMH rechargeable batteries
- Battery backup operating time
~ 24 h when fully charged
- Battery backup charging time
~ 10 h from fully depleted

Dimensions and weight

- Height: 108 mm, 4.3"
- Width: 121 mm, 4.7"
- Depth: 92 mm, 3.6"
- Weight: 390 g, 13.7 oz. incl. batteries

Display

- Type: Twisted Nematic LCD
- Adjustable backlight in 5 steps
- Display timeout: 8 seconds

Alarm and snooze

- Alarm timeout: 20 minutes
- Decreasing snooze time interval
from 9 to 2 minutes
- Snooze timeout: 20 minutes

Output signals

- Sound
100 dB @ 10 cm, 950 Hz – 3 kHz
- Four high-intensity flashing LEDs
- Bed shaker power: 2.0 – 4.0 VDC
The bed shaker emits a sound

Night light

- Built in night light that guides you
back to bed with a mild blue light
- Type: Electro Luminescent light (EL)
- Night light timeout
On mains power: 1 hour
On backup battery: 15 minutes


Accessories

- BE1271 Bed shaker without sound
- BE9250 Mobile phone sensor

Alarm clock Pro


Getting started

- 1 Pull the battery tab on the bottom of the alarm clock.
- 2 Connect the bed shaker on the back of the alarm clock.
- 3 Connect the power supply to the alarm clock and the mains outlet.
- 4 Tuck the bed shaker under the pillow or mattress and place the alarm clock on the bedside table.




Setting the time

Press the **left** dial and turn it to set hours.
To set minutes, press and turn the dial again.
Press once again to save your settings.




Setting the alarm

Press the **right** dial and turn it to set hours.
To set minutes, press and turn the dial again.
Press once again to save your settings.




Activating the alarm

Press the alarm on/off button to activate the alarm.
The alarm indicator lights up in red. To turn off the alarm, press the button again.



Using the snooze and night light

Press the snooze button briefly to snooze the alarm.
Press and hold the snooze button for 3 seconds to turn on the night light. Press the button again to turn it off.



Alarm clock Pro

Settings

Flash and sound on/off

Press the flash and sound on/off button marked with  on the back of the alarm clock repeatedly to toggle between the options. A  symbol will appear on the clock face when the flash is turned off and a  symbol when the sound is muted.

Backlight intensity

Press the backlight button marked with  on the back of the alarm clock repeatedly to adjust the intensity in five steps.


Time format

Press the time format button marked with **12/24h** on the back of the alarm clock to toggle between a 24h and a 12h setting.

Alarm clock accessories

The alarm clock can be complemented with the following accessories:

- **BE9105 Telephone cord**
Use it to connect the landline telephone to the alarm clock RJ11 input and be alerted when the telephone rings.
- **BE9250 Mobile phone sensor**
Connect it to the ext. trig. input and place it on the display to be alerted by incoming calls or messages.
- **BE9024 Contact mat**
Connect it to the ext. trig. input to be alerted when your spouse leaves the bed.



Troubleshooting

If	Try this
The alarm clock seems to be turned off	<ul style="list-style-type: none">▪ Check that the power supply is connected correctly, see Getting started.▪ Charge the backup batteries for a couple of hours.
The  symbol on the clock face starts to blink	<ul style="list-style-type: none">▪ The power supply is disconnected and the backup batteries are nearly depleted. Connect the power supply and charge the backup batteries for a couple of hours.
A  symbol appears on the clock face	<ul style="list-style-type: none">▪ The alarm clock detects no backup batteries. Pull the battery tab, see Getting started. If the problem remains, check the backup batteries.
A  symbol appears on the clock face	<ul style="list-style-type: none">▪ The flash is turned off. Press the flash and sound on/off button marked with  until the symbol disappears if you wish to turn it back on.
A  symbol appears on the clock face	<ul style="list-style-type: none">▪ The sound is muted. Press the flash and sound on/off button marked with  until the symbol disappears if you wish to turn it back on.
The display is too bright or too dark	<ul style="list-style-type: none">▪ Press the backlight button marked with  on the back of the alarm clock repeatedly to adjust the intensity in five steps.
The bed shaker does not vibrate	<ul style="list-style-type: none">▪ Make sure it's connected properly to the alarm clock, see Getting started.
The alarm volume is too low	<ul style="list-style-type: none">▪ The volume increases gradually and reaches over 100 dB.